



# LINEA: NO/NC 10A change-over button white

#### 30010.B

Wiring devices / Traditional wiring devices / LINEA / Devices

### NO/NC 10A change-over button white

1P NO/NC change-over 10 A 250 V~ lightable push button, replaceable button, white


#### **Product Status**

3 - Active

### Minimum order quantity

1 NR

# Drawings



Space view





3D View

### Technical data

Class group: Domestic switching devices

Class: Push button

**Assembly arrangement**: Modular device for domestic switching devices

Model: Other

Method of operation: Push button

Number of contacts as normally closed contact: 0
 Number of contacts as normally open contact: 1
 Number of contacts as change-over contact: 0

Number of revolving contacts: 0

Contactless type: No
Number of rockers: 1
Number of poles: 1
Nominal voltage: 250 V
Rated current: 10,00 A
With lighting: No
With light source: No
With signal lamp: No

Feedback-signal contact: No
Connection type: Screwed terminal
Mounting method: Flush-mounted

**Type of fastening**: Engage (snap)

Material: Plastic

Material quality: Thermoplastic

Halogen free: Yes

**Anti-bacterial treatment**: No **Surface protection**: Untreated

Surface finishing: Matt

**Colour**: White

RAL-number (similar): 9016

**Transparent**: No

Label space/information surface: No

Imprint: None

• Suitable for degree of protection (IP): IP40

Device width: 22,30 mm Device height: 52,80 mm Device depth: 39,70 mm

Compatible with Apple HomeKit: No
 Compatible with Google Assistant: No
 Compatible with Amazon Alexa: No

IFTTT support available: No

### Certifications

00. CE Marking - EU

01. IMQ - Italy (download)

37. Marking - Morocco

96. Electrotechnical expert (download)

99. WEEE Directive (download)

## **Packaging**



**Code** 8007352713369 **Quantity** 1 NR

Dim. 4.6x2.7x5.6 [cm] Weight 31.4 [g]

**Code** 8007352713376

**Quantity** 50 NR

**Dim.** 23.8x14.8x12.5 [cm]

**Weight** 1,687 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.