



## LINEA: Electromech.badge switch 2M canvas

---

### 30403.C

Wiring devices / Traditional wiring devices / LINEA / Devices

#### Electromech.badge switch 2M canvas

Upright electronic badge switch, 4 A 250 V~ NO change-over relay output (NON SELV), 120-230 V~ 50-60 Hz power supply, pocket lighting to be visible in darkness, trimmer for adjusting switch-off time after removing the card, canvas - 2 modules. Supplied without ISO card (badge)

#### Product Status

3 - Active

#### Minimum order quantity

1 NR

#### Sheets, Manuals, Documentation

- [Light Multilanguage instructions sheet \(709 kb\)](#)
- [Full Multilanguage instructions sheet \(1127 kb\)](#)

#### Drawings




## Technical data

- **Class group:** Alarm installations, emergency call and signalling
- **Class:** Access control system
- **Standalone:** Yes
- **Networkable:** No
- **PC-binding:** No
- **Type of interface:** None
- **Reading strategy:** Data medium
- **Signalling:** None
- **Mounting method:** Flush-mounted
- **Operating voltage AC 50 Hz:** 250,00 - 250,01 V
- **Operating voltage AC 60 Hz:** 250,00 - 250,01 V
- **Operating temperature:** 5 - 35 °C
- **Degree of protection (IP):** IP20
- **Colour:** Other
- **Model:** Reader
- **Material:** Plastic
- **Power over Ethernet (PoE):** None
- **Width:** 44,80 mm
- **Height:** 52,80 mm
- **Depth:** 36,10 mm
- **Compatible with Apple HomeKit:** No
- **Compatible with Google Assistant:** No
- **Compatible with Amazon Alexa:** No
- **IFTTT support available:** No
- **VdS class:** None

## Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 99. WEEE Directive ([download](#))

## Packaging



**Code** 8007352690257  
**Quantity** 1 NR  
**Dim.** 6x5.4x5.2 [cm]  
**Weight** 55.45 [g]



**Code** 8007352690264  
**Quantity** 10 NR  
**Dim.** 28.1x13.1x6 [cm]  
**Weight** 554.5 [g]



**Code** 8007352690271  
**Quantity** 120 NR  
**Dim.** 38.5x29x30 [cm]  
**Weight** 6,654 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).