



PLANA: TORCIA LED emergency lamp 2M

14397

Wiring devices / Traditional wiring devices / PLANA / Devices

TORCIA LED emergency lamp 2M

Product Status

3 - Active

Minimum order quantity

10 NR

Sheets, Manuals, Documentation

- Light multilanguage instructions sheet (640 kb)
- Full Multilanguage instruction sheet (1663 kb)

Drawings



Technical data

- Class group: Luminaires
- Class: Emergency luminaire
- Mounting method: Surface mounting/recessed mounting
- **Function**: Escape route lighting
- Suitable for labelling type: Other
- With pictogram: No
- Monitoring equipment: None
- With remote switch connection: Yes
- With remote control: No
- Power supply system: Peripheral (individual battery)
- Battery quality: Lithium-ions
- Lamp type: LED not exchangeable
- With light source: Yes
- Suitable for number of light sources: 1
- Lamp holder: Other
- Number of lighting heads: 2
- Housing colour: Colourless
- Material cover: Without cover
- Voltage type: AC
- Nominal voltage: 100,00 240,00 V

Certifications

- 00. CE Marking EU
- 37. Marking Morocco

Packaging



Code	8007352721357
Quantity	1 NR
Dim.	6x5.4x5.2 [cm]
Weight	68 [g]




 Code
 8007352721364

 Quantity
 10 NR

 Dim.
 28.1x13.1x6 [cm]

 Weight
 753.8 [g]



- **Exchangeable control gear**: No
- Light distributor: Other
- Degree of protection (IP): IP40
- Degree of protection (NEMA): Other
- Protection class: ||
- Max. system power: 1,00 W
- Nominal operation time: 250,00 251,00 h
- Width: 44,80 mm
- Height/depth: 46,90 mm
- Length: 49,00 mm
- Built-in width: 44,80 mm
- Built-in height/depth: 36,40 mm
- Built-in length: 49,00 mm
- Built-in diameter: 0 mm
- **Type of wiring**: Ending
- Number of poles: 0
- Conductor cross section: 250
- Connection type: Screw connection
- 96. Electrotechnical expert (download)
- 99. WEEE Directive (download)



 Code
 8007352721371

 Quantity
 120 NR

 Dim.
 38.5x29x30 [cm]

 Weight
 9,480 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported.Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed.For the terms of use of the information on the product info sheet see Conditions of Use.