



## IDEA: TV-RD-SAT through-line.out.2outs white

### 17067.10.B

Wiring devices / Traditional wiring devices / IDEA / Devices

### TV-RD-SAT through-line.out.2outs white

Coaxial TV-RD-SAT 5-2400 MHz socket outlet, through-line, demix, 2 outputs with male (TV-RD) and female F-type (SAT) connectors, connection attenuation 10 dB, white - 2 reduced modules

### Product Status

3 - Active

### Minimum order quantity

10 NR

### Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(905 kb\)](#)

### Drawings

### Technical data

- **Class group:** Antenna and satellite technique
- **Class:** Antenna socket box
- **Model:** TWIN end socket
- **Cover:** None
- **Tap loss at 860 MHz:** 11,20 dB
- **Tap loss at 2150 MHz:** 12,00 dB
- **Number of outlets:** 2
- **Through loss at 860 MHz:** 2,00 dB
- **Through loss at 2150 MHz:** 2,80 dB
- **Suitable for remote power supply:** No
- **Type of fastening:** Snap mounting (engagement)
- **Colour:** White
- **RAL-number (similar):** 9001
- **Material:** Plastic

### Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 99. WEEE Directive ([download](#))



## Packaging



**Code** 8007352400917  
**Quantity** 1 NR  
**Dim.** 5.1x4.3x5.3 [cm]  
**Weight** 83.7 [g]

**Code** 8007352401075  
**Quantity** 10 NR  
**Dim.** 26.9x11.6x4.9 [cm]  
**Weight** 889.8 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).