



EIKON: Flat 2P+E 16A FR SICURY outlet Next

22212.FL.N

Wiring devices / Traditional wiring devices / EIKON / Devices

Flat 2P+E 16A FR SICURY outlet Next

Product Status

3 - Active

Minimum order quantity

20 NR

Drawings



Technical data

Class group: Domestic switching devices

Class: Socket outlet

Model: Other

Number of active contacts (round): 0

Number of active contacts (flat): 0

With signal lamp: No Number of units: 1

Number of modules (module system): 2

Number of socket outlets switchable: 0

Number of phases: 2 Imprint/indication: None

Connection type: Screwed terminal

With hinged lid: No

With enhanced contact protection: Yes

Label space/information surface: Yes

Colour: Silver

RAL-number (similar): 9022

Metallic colour: No Transparent: No Lockable: No

Eject-mechanism: No **Insulated mounting**: No With function lighting: No

With orientation lighting: No

Over voltage protection: No Fault current protection: No

With miniature fuse: No

Special power supply: No special power supply

Mounting method: Flush-mounted

Type of fastening: Snap mounting (engagement)

Material: Plastic

Material quality: Thermoplastic

Halogen free: Yes

Surface protection: Lacquered

Surface finishing: Matt

Anti-bacterial treatment: No With loop through function: No

With on/off switch: No Rotated central insert: No Nominal current: 16 A Nominal voltage: 250 V Frequency: 50,00 - 60,00 HZ

Suitable for degree of protection (IP): IP20

Impact strength: Other Device width: 44,80 mm Device height: 49,00 mm Device depth: 46,80 mm

Min. depth of built-in installation box: 50 mm

Compatible with Apple HomeKit: No Compatible with Amazon Alexa: No Compatible with Google Assistant: No

IFTTT support available: No

For heavy conditions according to VDE: No

Certifications

00. CE Marking - EU

37. Marking - Morocco

99. WEEE Directive (download)

Packaging



Code Quantity Dim. Weight

8007352731851

5.1x4.3x5.3 [cm]

1 NR 46 [g]



8007352731868 Code Quantity 20 NR

26.9x11.6x9 [cm] Dim.

Weight 1,002 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.