



# LINEA: NO/NC 10A cord-change-over button

#### 30054.C

Wiring devices / Traditional wiring devices / LINEA / Devices

### NO/NC 10A cord-change-over button

1P NO/NC change-over 10 A 250 V $^{\sim}$  push button, with pull-cord and 1.5 m cord and knob, canvas


#### **Product Status**

3 - Active

### Minimum order quantity

20 NR

## Drawings



Space view





3D View

### Technical data

Class group: Domestic switching devices

Class: Push button

**Assembly arrangement**: Modular device for domestic switching devices

Model: Other

**Method of operation**: Push button

Number of contacts as normally closed contact: 1

Number of contacts as normally open contact: 1

Number of contacts as change-over contact: 0

Number of revolving contacts: 0

Contactless type: No Number of rockers: 1

Number of modules (module system): 100

Number of poles: 1 Nominal voltage: 250 V Rated current: 10,00 A With lighting: No With light source: No With signal lamp: No

Feedback-signal contact: No

Connection type: Screwed terminal Mounting method: Flush-mounted

**Type of fastening**: Engage (snap)

Material: Plastic

Material quality: Thermoplastic

Halogen free: Yes

Anti-bacterial treatment: No Surface protection: Untreated

Surface finishing: Matt

Colour: Beige

RAL-number (similar): 7032

Transparent: No

Label space/information surface: No

Imprint: None

Suitable for degree of protection (IP): IP40

Device width: 22,30 mm Device height: 52,80 mm Device depth: 29,20 mm

Compatible with Apple HomeKit: No Compatible with Google Assistant: No Compatible with Amazon Alexa: No

IFTTT support available: No

### Certifications

00. CE Marking - EU

01. IMQ - Italy (download)

37. Marking - Morocco

96. Electrotechnical expert (download)

99. WEEE Directive (download)

## **Packaging**



Code Quantity Weight

8007352690202

4.6x2.7x5.6 [cm] 34.4 [g]



Code Quantity Dim. Weight

8007352711785 10 NR 14.6x10x6.6 [cm] 393.2 [g]



Code 8007352690226 Quantity 120 NR Dim. 31x22x21 [cm] Weight 4,990 [g]

### Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.