



LINEA: 1P 10AX switch white

30060.B

Wiring devices / Traditional wiring devices / LINEA / Devices

1P 10AX switch white

1P 10 AX 250 V \sim switch, with two buttons, direction arrows and central OFF position, white. Max 100 W for lamps with built-in power supply unit (IEC 60669-1:2017)

Product Status

3 - Active

Minimum order quantity

10 NR

Drawings



Technical data

Class group: Domestic switching devices

Class: Push button

Assembly arrangement: Modular device for domestic switching devices

Model: Other

Method of operation: Push button

Number of contacts as normally closed contact: 0

Number of contacts as normally open contact: 0

Number of contacts as change-over contact: 0

Number of revolving contacts: 0

Contactless type: No Number of rockers: 1

Number of modules (module system): 100

Number of poles: 1 Nominal voltage: 250 V Rated current: 10,00 A With lighting: No With light source: No With signal lamp: No

Feedback-signal contact: No

Connection type: Screwed terminal Mounting method: Flush-mounted

Type of fastening: Engage (snap)

Material: Plastic

Material quality: Thermoplastic

Halogen free: Yes

Anti-bacterial treatment: No Surface protection: Untreated

Surface finishing: Matt

Colour: White

RAL-number (similar): 9016

Transparent: No

Label space/information surface: No

Imprint: None

Suitable for degree of protection (IP): IP40

Device width: 22,30 mm Device height: 52,80 mm Device depth: 30,90 mm

Compatible with Apple HomeKit: No Compatible with Google Assistant: No Compatible with Amazon Alexa: No

IFTTT support available: No

Certifications

00. CE Marking - EU

37. Marking - Morocco

96. Electrotechnical expert (download)

99. WEEE Directive (download)

Packaging



Code Quantity 1 NR

8007352684157

Dim. 4.6x2.7x5.6 [cm] Weight 27.8 [g]



Code Quantity Dim.

10 NR 14.6x10x6.6 [cm] Weight 324.8 [g]

8007352684164

Code Quantity Dim. Weight

8007352684171 120 NR 31x22x21 [cm] 4,175 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.