



LINEA: Two interlocked NO+NO 10A button white

30062.B

Wiring devices / Traditional wiring devices / LINEA / Devices

Two interlocked NO+NO 10A button white

Two interlocked 1P NO + 1P NO 10 A 250 V $^{\sim}$ buttons, with direction arrows, white

Product Status

3 - Active

Minimum order quantity

20 NR

Drawings



Technical data

Class group: Domestic switching devices

Class: Push button

Assembly arrangement: Modular device for domestic switching devices

Model: Other

Method of operation: Push button

Number of contacts as normally closed contact: 0

Number of contacts as normally open contact: 2

Number of contacts as change-over contact: 0

Number of revolving contacts: 0

Contactless type: No Number of rockers: 1

Number of modules (module system): 100

Number of poles: 1 Nominal voltage: 250 V Rated current: 10,00 A With lighting: No With light source: No

With signal lamp: No Feedback-signal contact: No

Connection type: Screwed terminal Mounting method: Flush-mounted

Type of fastening: Engage (snap)

Material: Plastic

Material quality: Thermoplastic

Halogen free: Yes

Anti-bacterial treatment: No Surface protection: Untreated

Surface finishing: Matt

Colour: White

RAL-number (similar): 9016

Transparent: No

Label space/information surface: No

Imprint: None

Suitable for degree of protection (IP): IP40

Device width: 22,30 mm Device height: 52,80 mm Device depth: 29,85 mm

Compatible with Apple HomeKit: No Compatible with Google Assistant: No Compatible with Amazon Alexa: No

IFTTT support available: No

Certifications

00. CE Marking - EU

01. IMQ - Italy (download)

37. Marking - Morocco

, 96. Electrotechnical expert (download)

99. WEEE Directive (download)

Packaging



Code Quantity Weight

8007352691179

3.6x2.7x5.6 [cm] 27.6 [g]



Code Quantity Dim. Weight

8007352691186 20 NR 19.4x12.6x6.5 [cm] 620.6 [g]



Code Quantity Dim. Weight

8007352691193 200 NR 40x33.5x15 [cm] 6,630 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.